Model PCM-2A Para Contamination Monitor (GM Tube based)





Contamination Monitor PCM-2A

PCM-2A, Contamination monitor is used for measurement of radioactive contamination in Nuclear Power Plants, Nuclear Medicine Centers. This instrument is ideally suitable for scanning material, tools, clothing, personnel etc. It is a mains operated unit & includes nuclear detector (GM tube) assembly probe and processing electronics. Indication of CRM in ranges of 0 to 10, 100 or 1000 CPS is available on 96 mm X 96 mm square, taut band meter. Range Selector switch enables user to select CRM range or HV or Alarm Level in percentage.

Specifications (PCM-2A)

Detector Assembly (GM Tube)

Detectors Thin walled GM Tube / Pancake type Frikser arrangement

(Other GM detectors also can be offered as option)

Chrome plated brass tube with shield to prevent beta detection Housing 0 to 1000 Volts @ 1 mA internally set at detector operating voltage **HV** supply

CRM and Failure Alarms

Alarms Beeper and Red Flasher ON when count rate exceeds preset level

Set Point Adjustment Adjustment over entire range

Reset Push switch to clear alarm condition

Failure Alarm Red Flasher alarm is continuously ON if no pulse is detected within 60 secs

No Pulse Alarm Continuous ON Red LED

Count Rate Meter

Linear CRM Three ranges of 0-10, 100 and 1000 CPS switch selectable

±5 % of full scale Accuracy

Taut band 96 x 96 mm square panel meter, 270° deflection pointer Display

movement for indication of CRM, HV and Alarm Level

General

Powder coated Aluminium table top box **Enclosure**

300 L X 230 W X 155 H mm **Dimensions**

Weight Approx. 4 Kg

240 V (± 10%), 50 Hz, single phase mains supply **Power**

Due to continuous R&D, specifications are likely to change without notice

Manufactured By:

Electronic Enterprises (I) Pvt. Ltd. Para Electronics Manufacturing Division

306, Nimesh Industrial Estate Vidyalaya Marg, Mulund (East)

Mumbai 400 081

Phone: 022-2563 5600/2741

Fax : 022-2563 7835 Website: www.eeipl.in

Email: pemd@eeipl.in

Mumbai 022-25639904

eemulund@eeipl.in

Kolkata 033-25770551 eecal@eeipl.in

BRANCHES Hyderabad

040-23243352 eehyd@eeipl.in

Delhi

Bangalore 080-23380451 eebng@eeipl.in

Kota

0744-2501113 011-27240436 eedelhi@eeipl.in eekota@eeipl.in